

Digital multimeter

- Can measure voltages up to 1,000 V
- Resistance measurement and semiconductor test
- Capacitance measurement
- MAX/MIN memory
- HOLD function
- Battery status display
- Carry case included

Multimeter 1037

Digital multimeter



- Voltage measurement
- Current measurement
- Resistance measurement
- Non-contact voltage measurement is possible
- Extensive accessories



Multimeter 2606

Digital clamp-on measuring device



- Currents up to 1,000 A measurable with clamp-on attachment
- Frequency measurement
- Voltage measurement
- Current measurement
- PEAK function



Technical data

DC voltage measuring range
Resolution of DC voltage
AC voltage measuring range
Resolution of AC voltage
Measured current value, max.
Opening width of current-measuring clamp-on attachment
Resistance measuring range
Measured capacitance value, min.
Frequency range, min.
Temperature measuring range
Operating temperature, min.
Approvals
Weight
Note

MULTIMETER 1037
0,2 - 1,000 V
0,2 - 750 V
200 A
23 mm
0,2...200 kΩ
...200 μF
50...500 Hz
... °C
0...50 °C
EN/IEC 61010-1
258 g

MULTIMETER C 2606
0,4 - 1,000 V
± 0,5 %
0,4 - 1,000 V
± 0,5 %
1,000 A
57 mm
0,4...40 MΩ
40...4 μF
0,1...400 kHz
... °C
0...50 °C
VDE 0680, Part 5
540 g

Ordering data

Version
Note

Type	Qty.	Order No.
MULTIMETER 1037	1	9423580000

Type	Qty.	Order No.
MULTIMETER C 2606	1	9427370000

Accessories

Note

Type	Qty.	Order No.
ZUB MULTI 1037	1	9205460000
9-V block battery	1	9004810000
Carrying case and pliers adapter are not included in the delivery		

Type	Qty.	Order No.
ZUB TEMPASER	1	9205270000
9-V block battery	1	9004810000
Carrying case not included		